

NOTES

- See Contract for head type, mounting height, and orientation.
- 2. All nipples, fittings, and center pipes shall be 1 1/2" (in) diameter.
- 3. Install neoprene gasket inside head when flanged elbows are supplied.
- 4. Extend wire sheath a minimum of 1" (in) inside all signal and sign housings and terminal compartments.
- Apply bead of silicone to the serrated ring and around the perimeter of all top openings prior to installation of fittings.
- 6. See Standard Specification 9-29.16 for backplate requirements. Where required, prismatic sheeting shall be applied in accordance with the manufacturer's recommendations. The application surface of the backplate shall be cleaned, degreased with isopropyl alcohol, and dried prior to application of the sheeting.
- 7. Drill a 1/4" (in) drain hole in the bottom of each signal display assembly, and one in the bottom of each pedestrian head. When signal display assembly is mounted horizontally, drill a 1/4" (in) drain hole at the lowest point of each section of the signal assembly.



SIGNAL HEAD MOUNTING DETAILS ~ POLE AND POST TOP MOUNTINGS STANDARD PLAN J-75.10-02

SHEET 1 OF 1 SHEET

APPROVED FOR PUBLICATION

STATE DESIGN ENGINEER

Washington State Department of Transportation